

# Andhra Pradesh State Council of Higher Education

**Notations :**

- 1.Options shown in green color and with ✓ icon are correct.
- 2.Options shown in red color and with ✖ icon are incorrect.

<b>Question Paper Name :</b>	CS2
<b>Subject Name :</b>	Computer Science and Information Technology
<b>Creation Date :</b>	2025-06-06 16:37:28
<b>Duration :</b>	120
<b>Total Marks :</b>	120
<b>Display Marks:</b>	No
<b>Share Answer Key With Delivery Engine :</b>	Yes
<b>Change Font Color :</b>	No
<b>Change Background Color :</b>	No
<b>Change Theme :</b>	No
<b>Help Button :</b>	No
<b>Show Reports :</b>	No
<b>Show Progress Bar :</b>	No

## Computer Science and Information Technology

<b>Group Number :</b>	1
<b>Group Id :</b>	83189668
<b>Group Maximum Duration :</b>	0
<b>Group Minimum Duration :</b>	120
<b>Show Attended Group? :</b>	No
<b>Edit Attended Group? :</b>	No

Break time : 0  
Group Marks : 120

## Computer Science and Information Technology

Section Id : 83189668  
Section Number : 1  
Section type : Online  
Mandatory or Optional : Mandatory  
Number of Questions : 120  
Number of Questions to be attempted : 120  
Section Marks : 120  
Maximum Instruction Time : 0  
Sub-Section Number : 1  
Sub-Section Id : 83189668  
Question Shuffling Allowed : Yes

Question Number : 1 Question Id : 8318968041 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

In how many ways can a chairperson, a secretary, and a treasurer be chosen from a group of 10 people, if each person can hold only one position?

Options :

1. ✘ 840

2. ✘ 5040

3. ✘ 1240

4. ✔ 720

Question Number : 2 Question Id : 8318968042 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

A sub graph H of a graph G is called a clique if \_\_\_\_\_.

Options :

1. ✔  $V(G) = V(H)$

2. ✘  $V(H) \subseteq V(G)$

3. ✘ H contain all edges of G

4. ✘ H is also a complete graph

Question Number : 3 Question Id : 8318968043 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes

Correct Marks : 1 Wrong Marks : 0

For a given graph  $G$  having  $v$  vertices and  $e$  edges which is connected and has no cycles, which of the following statements is true?

Options :

1. ✘  $v = e$

2. ✔  $v = e + 1$

3. ✘  $v + 1 = e$

4. ✘  $v = e - 1$

Question Number : 4 Question Id : 8318968044 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes

Correct Marks : 1 Wrong Marks : 0

Assume  $G$  is a simple undirected graph and some vertices of  $G$  are of odd degree. Add a node  $v$  to  $G$  and make it adjacent to each odd degree vertex of  $G$ , then the resultant graph is sure to be \_\_\_\_\_.

Options :

1. ✓ Euler
2. ✗ complete
3. ✗ Hamiltonian
4. ✗ clique

Question Number : 5 Question Id : 8318968045 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

Dijkstra's algorithm fails for graphs with \_\_\_\_\_.

Options :

1. ✓ Negative weights
2. ✘ Disconnected components
3. ✘ Directed edges
4. ✘ Self-loops

Question Number : 6 Question Id : 8318968046 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

In propositional logic  $P \leftrightarrow Q$  is equivalent to ( $\sim$  denotes NOT)\_\_\_\_\_.

Options :

1. ✘  $\sim(P \vee Q) \wedge \sim(Q \vee P)$
2. ✓  $(\sim P \vee Q) \wedge (\sim Q \vee P)$

3. ✘  $(P \vee Q) \wedge (Q \vee P)$

4. ✘  $\sim(P \vee Q) \rightarrow \sim(Q \vee P)$



Question Number : 7 Question Id : 8318968047 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes

Correct Marks : 1 Wrong Marks : 0

The Boolean function  $\sim((\sim P \wedge Q) \wedge \sim(\sim P \wedge \sim Q)) \vee (P \vee R)$  is equal to the Boolean function:

Options :

1. ✘ Q

2. ✘ R

3. ✘  $P \vee Q$

4. ✔ P

Question Number : 8 Question Id : 8318968048 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes

Correct Marks : 1 Wrong Marks : 0

A graph is self-complementary if it is isomorphic to its complement.

For all self-complementary graphs on  $n$  vertices,  $n$  is \_\_\_\_\_.

Options :

1. ✘ a multiple of 4
2. ✘ even
3. ✘ odd
4. ✔ congruent to 0 mod 4 or 1 mod 4

Question Number : 9 Question Id : 8318968049 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

Suppose  $R_1$  and  $R_2$  are reflexive relations on a set  $A$ .

Which of the following statements is correct?

Options :

1. ✘  $R_1 \cap R_2$  is reflexive and  $R_1 \cup R_2$  is irreflexive
2. ✘  $R_1 \cap R_2$  is irreflexive and  $R_1 \cup R_2$  is reflexive

Both  $R_1 \cap R_2$  and  $R_1 \cup R_2$  is irreflexive

3. ✘

Both  $R_1 \cap R_2$  and  $R_1 \cup R_2$  is reflexive

4. ✔

Question Number : 10 Question Id : 8318968050 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

There are three cards in a box, Both sides of one card are black, both sides of one card are red, and the third card has one black side and one red side. We pick a card at random and observe only one side. What is the probability that the opposite side is the same colour as the one side we observed?

Options :

1. ✘  $3/4$

2. ✘  $2/3$

3. ✘  $1/2$

4. ✔  $1/3$

Question Number : 11 Question Id : 8318968051 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

An 8-bit number X is 00001100, then -X is in 1 s complement  
is \_\_\_\_\_.

Options :

1. ✘ 12 in binary

2. ✔ 243 binary code in 8 bit

3. ✘ 111011100

4. ✘ 111110101

Question Number : 12 Question Id : 8318968052 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

Assuming 5-bit addition is done on registers, the sum  $12+7$  leads to\_\_\_\_\_.

Options :

1. ✓ Overflow
2. ✗ -12
3. ✗ 19
4. ✗ -14

Question Number : 13 Question Id : 8318968053 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

In a 4-bit ripple carry adder, the worst-case delay occurs when\_\_\_\_\_.

Options :

1. ✘ all input bits are 0
2. ✔ a carry propagates through all full adders
3. ✘ no carry is generated
4. ✘ the sum exceeds 15

Question Number : 14 Question Id : 8318968054 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

The output of a JK flip-flop for inputs  $J=1$ ,  $K=1$  and clock transition from 1 to 0 is \_\_\_\_\_.

Options :

1. ✘ no change

2. ✘ reset

3. ✔ toggle

4. ✘ set

Question Number : 15 Question Id : 8318968055 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

The IEEE 754 single-precision floating-point representation of 0.375  
is \_\_\_\_\_.

Options :

1. ✘ 0 01111100 100000000000000000000000

2. ✘ 0 01111101 100000000000000000000000

3. ✘ 0 01111101 110000000000000000000000

0 01111100 110000000000000000000000

4. ✓

Question Number : 16 Question Id : 8318968056 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

In a hardwired control unit, the sequence of control signals is generated by\_\_\_\_\_.

Options :

Microprogrammed ROM

1. ✘

State machine/circuitry

2. ✓

Operating system

3. ✘

Interrupt handler

4. ✘

Question Number : 17 Question Id : 8318968057 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

In DMA mode, the CPU is bypassed for data transfer between\_\_\_\_\_.

Options :

1. ✘ CPU and I/O devices
2. ✘ Registers and ALU
3. ✔ Memory and I/O devices
4. ✘ Cache and secondary storage

Question Number : 18 Question Id : 8318968058 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes Correct Marks : 1 Wrong Marks : 0

A 4-way set-associative cache with 256 blocks divides memory addresses into\_\_\_\_\_.

Options :

1. ✘ 256 sets
2. ✔ 64 sets
3. ✘ 4 sets
4. ✘ 16 sets

Question Number : 19 Question Id : 8318968059 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

$AB \oplus (A+B)$  is equivalent to \_\_\_\_\_.

Options :

1. ✔  $A^1B+AB^1$
2. ✘  $AB+A^1B^1$

3. ✘  $A^1B+A^1B$

4. ✘  $A+B$

Question Number : 20 Question Id : 8318968060 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

Which of these flip – flops cannot be used to construct a serial shift register?

Options :

1. ✘ D – flip flop

2. ✘ SR flip – flop

3. ✔ T flip – flop

4. ✘ JK flip – flop

Question Number : 21 Question Id : 8318968061 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes

Correct Marks : 1 Wrong Marks : 0

How many AND gates are required to realize  $Y = CD + EF + G$ ?

Options :

1. ✘ 4

2. ✘ 5

3. ✘ 3

4. ✔ 2

Question Number : 22 Question Id : 8318968062 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes

Correct Marks : 1 Wrong Marks : 0

The purpose of an interrupt vector table is to \_\_\_\_\_.

Options :

1. ✘ Store CPU registers during context switch

Map interrupt requests to service routine addresses

2. ✓

Hold page tables for virtual memory

3. ✗

Cache frequently used instructions

4. ✗

Question Number : 23 Question Id : 8318968063 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

What is the output of the following code fragment?

```
int x=24;  
printf("%d\n",printf("%3d %3d\n",x,x));
```

Options :

24 24

1. ✗ 10

24 24

2. ✘ 9

24 24

3. ✔ 8

4. ✘ Error

Question Number : 24 Question Id : 8318968064 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

How many times “*Hi*” message will be displayed when we execute the following for loop?

```
int i;  
for(i=0;i%2?0:1;i++)  
printf("Hi \n");
```

Options :

1. ✘ 3
2. ✘ 2
3. ✔ 1
4. ✘ 0

Question Number : 25 Question Id : 8318968065 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

If one wants to add and delete elements quickly without reshuffling the rest, then which data structure suits the best?

Options :

1. ✔ Linked list
2. ✘ Tree

B-Tree

3. ✘

Array

4. ✘

Question Number : 26 Question Id : 8318968066 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

The height of a binary tree with 31 nodes (assuming no single-child nodes) is \_\_\_\_\_.

Options :

4

1. ✔

5

2. ✘

6

3. ✘

7

4. ✘

Question Number : 27 Question Id : 8318968067 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes

Correct Marks : 1 Wrong Marks : 0

In a max-heap, the largest element is always located at the \_\_\_\_\_.

Options :

1. ✘ leftmost leaf
2. ✘ rightmost leaf
3. ✔ root node
4. ✘ middle of the heap

Question Number : 28 Question Id : 8318968068 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes

Correct Marks : 1 Wrong Marks : 0

The recurrence  $T(n)=2T(n/2)+n$  has a solution of \_\_\_\_\_.

Options :

1. ✘  $O(n)$

2. ✔  $O(n \log n)$

3. ✘  $O(n^2)$

4. ✘  $O(\log n)$

Question Number : 29 Question Id : 8318968069 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

What is the time complexity to insert an element at the beginning of a dynamic array?

Options :

1. ✘  $O(1)$

2. ✔  $O(n)$

3. ✘  $O(n \log n)$

4. ✘  $O(\log n)$

Question Number : 30 Question Id : 8318968070 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

The inorder traversal of a BST gives elements in \_\_\_\_\_.

Options :

1. ✘ level order

2. ✔ ascending order

3. ✘ descending order

4. ✘ random order

Question Number : 31 Question Id : 8318968071 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes

Correct Marks : 1 Wrong Marks : 0

A threaded binary tree is a binary tree in which every node that does not have right child has a thread to its \_\_\_\_\_.

Options :

1. ✘ Pre-order successor
2. ✔ In-order successor
3. ✘ In-order predecessor
4. ✘ Post-order successor

Question Number : 32 Question Id : 8318968072 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

Which notation represents the tightest upper bound of an algorithm's running time?

Options :

1. ✘  $O(n)$

2. ✘  $\Omega(n)$

3. ✔  $\Theta(n)$

4. ✘  $\omega(n)$

Question Number : 33 Question Id : 8318968073 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

The minimum possible time complexity to sort  $n$  integers in the range  $[1, n^2]$  is \_\_\_\_\_.

Options :

1. ✔  $O(n)$

2. ✘  $O(n \log n)$

3. ✘  $O(n^2)$

4. ✘  $O(\log n)$

Question Number : 34 Question Id : 8318968074 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

The greedy approach is optimal for \_\_\_\_\_.

Options :

1. ✘ 0/1 Knapsack

2. ✔ Fractional Knapsack

3. ✘ Longest Increasing Subsequence

4. ✘ Matrix Chain Multiplication

Question Number : 35 Question Id : 8318968075 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

Best case complexity of insertion sorting is \_\_\_\_\_.

Options :

1. ✓  $O(n)$

2. ✗  $O(n \log n)$

3. ✗  $O(n^2)$

4. ✗  $O(\log n)$

Question Number : 36 Question Id : 8318968076 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

A problem is NP-complete if it is \_\_\_\_\_.

Options :

1. ✗ solvable in polynomial time

2. ✓ NP-hard and is NP

3. ✗ reducible to P

4. ✗ Non-deterministic but decidable

Question Number : 37 Question Id : 8318968077 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

The time complexity to compute the 15<sup>th</sup> Fibonacci number using dynamic programming is \_\_\_\_\_.

Options :

1. ✗  $O(1)$

2. ✓  $O(n)$

3. ✗  $O(n \log n)$

$O(\log n)$

4. ✘

Question Number : 38 Question Id : 8318968078 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

One way to build a heap is to start at the end of the array (the leaves) and push each new value up to the root. Its time complexity is

Options :

$O(n)$

1. ✘

$O(\log n)$

2. ✘

$O(n \log n)$

3. ✔

$O(n^2 \log n)$

4. ✘

Question Number : 39 Question Id : 8318968079 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

If the recursive call keeps calculating the same things over and over again, we can use \_\_\_\_\_ which stores partial results already calculated and to be used again.

Options :

Divide and conquer algorithm

1. ✘

Recursive

2. ✘

Dynamic Programming

3. ✔

Greedy method

4. ✘

Question Number : 40 Question Id : 8318968080 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

The \_\_\_\_\_ process updates the costs of all the vertices  $V$ , connected to a vertex  $U$ , if we could improve the best estimate of the shortest path to  $V$  by including  $(U,V)$  in the path to  $V$ .

Options :

1. ✓ relaxation
2. ✗ improvement
3. ✗ shortening
4. ✗ costing

Question Number : 41 Question Id : 8318968081 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

The minimum number of states in a DFA accepting

$L = \{w \mid w \text{ ends with } 01\}$  over  $\Sigma = \{0,1\}$  is:

Options :

1. ✘ 2

2. ✔ 3

3. ✘ 4

4. ✘ 5

Question Number : 42 Question Id : 8318968082 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

The language  $L = \{\langle M \rangle \mid M \text{ halts on all inputs}\}$  is \_\_\_\_\_.

Options :

1. ✘ decidable

2. ✔ undecidable but recognizable

3. ✘ not recognizable

4. ✘ regular

Question Number : 43 Question Id : 8318968083 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

Inherited attributes in SDTs are used for \_\_\_\_\_.

Options :

1. ✘ passing information up the parse tree

2. ✔ passing information down the parse tree

3. ✘ storing symbol table entries

4. ✘ generating target code

Question Number : 44 Question Id : 8318968084 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

The output of a syntax-directed translation scheme is \_\_\_\_\_.

Options :

Abstract Syntax Tree

1. ✘

Three Address Code

2. ✘

Postfix Notation

3. ✘

Depends on the SDT rules

4. ✔

Question Number : 45 Question Id : 8318968085 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

Subset Construction method refers to \_\_\_\_\_.

Options :

Conversion of NFA to DFA

1. ✓

DFA minimization

2. ✘

Eliminating Null references

3. ✘

DFA to NFA

4. ✘

Question Number : 46 Question Id : 8318968086 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

The maximum number of transitions which can be performed over a state in a DFA?  $\Sigma = \{a, b, c\}$

Options :

8

1. ✘

2

2. ✘

3. ✓ 3

4. ✘ 7

Question Number : 47 Question Id : 8318968087 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

Which of the following is a regular language?

Options :

A string whose length is a sequence of prime numbers

1. ✘

A string with substring  $ww^r$

2. ✘

A palindrome

3. ✘

A string with even number of zero's

4. ✓

Question Number : 48 Question Id : 8318968088 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes

Correct Marks : 1 Wrong Marks : 0

The minimum number of nodes in a DFA that recognizes strings over  $\{a, b\}$  with length mod  $3 = 0$  are \_\_\_\_\_.

Options :

- 1. ✘ 4
- 2. ✘ 2
- 3. ✔ 3
- 4. ✘ 1

Question Number : 49 Question Id : 8318968089 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes

Correct Marks : 1 Wrong Marks : 0

If the production rules are given as:

$$S \rightarrow XY \mid W$$

$$X \rightarrow aXb \mid \varepsilon$$

$$Y \rightarrow cY \mid \varepsilon$$

$$W \rightarrow aWc \mid Z$$

$$Z \rightarrow bZ \mid \varepsilon$$

Then the language generated by these rules is \_\_\_\_\_.

Options :

1. ✘  $\{a^i b^j c^k / i, j, k \geq 0\}$
2. ✘  $\{a^i b^j c^k / i, j, k \geq 1\}$
3. ✘  $\{a^i b^j c^k / i, j, k \geq 0, i=j \text{ or } i=k\}$
4. ✔  $\{a^i b^j c^k / i, j, k \geq 0, i=j \text{ or } i \neq k\}$

Question Number : 50 Question Id : 8318968090 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

Let  $P$  be a regular language and  $Q$  be a context free language such that  $Q$  is subset of  $P$ . Then which of the following is ALWAYS regular?

Options :

1. ✘  $P \cap Q$

2. ✘  $P - Q$

3. ✔  $\Sigma^* - P$

4. ✘  $\Sigma^* - Q$

Question Number : 51 Question Id : 8318968091 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

Which one of the following is FALSE?

Options :

1. ✘ Every NFA can be converted to an equivalent PDA
2. ✘ Complement of every context free language is recursive
3. ✘ There is a unique minimal DFA for every regular language
4. ✔ Every nondeterministic PDA can be converted to equivalent deterministic PDA

Question Number : 52 Question Id : 8318968092 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

Which of the following is not a three-address code statement?

Options :

1. ✘  $x = y + z$

2. ✘ if x goto L

3. ✘  $x = *y$

4. ✔  $x = y ** z$

Question Number : 53 Question Id : 8318968093 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

Which of the following is not shared among threads in the same process?

Options :

1. ✘ Heap memory

2. ✔ Stack

3. ✘ File Descriptors

4. ✘ Code section

Question Number : 54 Question Id : 8318968094 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

The primary advantage of user-level threads over kernel-level threads is\_\_\_\_\_.

Options :

1. ✓ lower context-switch overhead
2. ✘ better parallelism on multicore CPUs
3. ✘ no need for synchronization
4. ✘ higher priority scheduling

Question Number : 55 Question Id : 8318968095 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

A program uses environment variables to\_\_\_\_\_.

Options :

1. ✘ store data between login sessions
2. ✔ pass configuration settings to other programs
3. ✘ store data persistently
4. ✘ pass data to the operating system

Question Number : 56 Question Id : 8318968096 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

Which is not a CPU scheduling criterion?

Options :

1. ✘ CPU utilisation
2. ✔ Reliability

Response time

3. ✘

Waiting time

4. ✘

Question Number : 57 Question Id : 8318968097 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

Among priority inversion between two processes, one with high priority and other with low priority that share a critical section will cause which of the following problem?

Options :

High priority process executes before low priority process and finishes faster than it should.

1. ✘

Low priority process executes before high priority process and finishes faster than it should.

2. ✘

High priority process waits for low priority process to finish,  
but the low priority process never gets scheduled.

3. ✓

Low priority process changes priority temporary to the  
priority of the high priority process.

4. ✘

Question Number : 58 Question Id : 8318968098 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

A currently running process can be put on a ready queue or one of  
the I/O queues by each of the following except\_\_\_\_\_.

Options :

1. ✘ the process issued an i/o request

2. ✓ the process did an illegal memory access

3. ✘ there was an interrupt

the process issued a system call

4. ✘

Question Number : 59 Question Id : 8318968099 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

Which of the following component of program state is shared across threads in a multithreaded process?

Options :

Registers

1. ✘

Auto variables

2. ✘

Heap memory

3. ✔

Stack memory

4. ✘

Question Number : 60 Question Id : 8318968100 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

Which of the following frees the CPU from having to deal with transfer of memory to or from I/O device?

Options :

1. ✘ Interrupts
2. ✔ Direct Memory Access
3. ✘ Buffer cache
4. ✘ Device Driver

Question Number : 61 Question Id : 8318968101 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

In FCFS, I/O bound processes may have to wait long in the ready queue waiting for a CPU bound job to finish. This is known as \_\_\_\_\_.

Options :

1. ✘ Aging
2. ✔ Convoy effect
3. ✘ Priority inversion
4. ✘ Belady's anomaly

Question Number : 62 Question Id : 8318968102 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

In general, there will be \_\_\_\_\_ inodes than directories in Unix  
File system.

Options :

1. ✘ zero
2. ✘ less

3. ✘ same

4. ✔ more

Question Number : 63 Question Id : 8318968103 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

To ensure that the \_\_\_\_\_ condition never occurs in the system,  
we must guarantee that, whenever a process requests a resource, it  
does not have any other resource.

Options :

1. ✘ mutual exclusion

2. ✘ no-preemption

3. ✘ circular wait

4. ✓ hold and wait

Question Number : 64 Question Id : 8318968104 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

A \_\_\_\_\_ architecture assigns only a few essential functions to the kernel, including address spaces, Interprocess communication (IPC) and basic scheduling.

Options :

1. ✘ monolithic kernel
2. ✓ micro kernel
3. ✘ macro kernel
4. ✘ mini kernel

Question Number : 65 Question Id : 8318968105 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes

Correct Marks : 1 Wrong Marks : 0

Among the four criteria for synchronization mechanism, which of the two criteria are mandatory?

Options :

Mutual Exclusion and Progress

1. ✓

Progress and Architectural neural

2. ✘

Bounded wait and mutual exclusion

3. ✘

Bounded wait and progress

4. ✘

Question Number : 66 Question Id : 8318968106 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

Which SQL operation is not part of the ACID properties?

Options :

1. ✘ COMMIT
2. ✘ ROLLBACK
3. ✔ CREATE INDEX
4. ✘ SAVEPOINT

Question Number : 67 Question Id : 8318968107 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

A B+ tree is preferred over a B-tree for databases because \_\_\_\_\_.

Options :

1. ✔ it supports range queries efficiently
2. ✘ it has a smaller node size

it allows faster insertion/deletion

3. ✘

it uses less disk space

4. ✘

Question Number : 68 Question Id : 8318968108 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

A relation  $R(A,B,C,D)$  with functional dependencies  $\{A \rightarrow B, B \rightarrow C\}$

is in \_\_\_\_\_.

Options :

1. ✘ 1NF but not 2NF

2. ✔ 2NF but not 3NF

3. ✘ 3NF but not BCNF

4. ✘ BCNF

Question Number : 69 Question Id : 8318968109 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

In two-phase locking (2PL), a transaction must be \_\_\_\_\_.

Options :

1. ✘ release all locks before acquiring new ones
2. ✔ acquire all locks before releasing any
3. ✘ use only shared locks
4. ✘ avoid deadlocks by timeouts

Question Number : 70 Question Id : 8318968110 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

The isolation level that prevents dirty reads but allows non-repeatable reads is \_\_\_\_\_.

Options :

read uncommitted

1. ✘

read committed

2. ✔

repeatable read

3. ✘

serializable

4. ✘

Question Number : 71 Question Id : 8318968111 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

The maximum number of keys in a B-tree of order 5 with height 3  
is \_\_\_\_\_.

Options :

31

1. ✘

2. ✓ 156

3. ✘ 624

4. ✘ 3125

Question Number : 72 Question Id : 8318968112 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

In \_\_\_\_\_ relation, each tuple has relation R within it.

Options :

1. ✘ primary

2. ✘ prime

3. ✓ nested

4. ✘ atomic

Question Number : 73 Question Id : 8318968113 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

The rule which states that addition of same attributes to the right side and left side will result in other valid dependency is classified as \_\_\_\_\_.

Options :

1. ✔ Augmentation rule
2. ✘ Inference rule
3. ✘ Referential rule
4. ✘ Reflexive rule

Question Number : 74 Question Id : 8318968114 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes

Correct Marks : 1 Wrong Marks : 0

The separation of the data definition from program is known

as \_\_\_\_\_.

Options :

Data dictionary

1. ✘

Data independence

2. ✔

Data integrity

3. ✘

Referential integrity

4. ✘

Question Number : 75 Question Id : 8318968115 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes

Correct Marks : 1 Wrong Marks : 0

Which is the candidate key for the relation  $R(ABCDE)$  with

functional dependencies  $F = \{A \rightarrow BC, B \rightarrow D, CD \rightarrow E, E \rightarrow A\}$

Options :

1. ✓ A
2. ✘ CD
3. ✘ B
4. ✘ E

Question Number : 76 Question Id : 8318968116 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

Natural Join can also be termed as \_\_\_\_\_.

Options :

1. ✘ combination of Union and Cartesian Product
2. ✘ combination of Selection and Cartesian Product

3. ✓ combination of Projection and Cartesian Product

4. ✘ combination of Projection and Union

Question Number : 77 Question Id : 8318968117 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

If  $A \rightarrow B$  has trivial functional dependency, then \_\_\_\_\_.

Options :

1. ✓ B is a subset of A

2. ✘ A is a subset of B

3. ✘ A is a subset of A'

4. ✘ B is a subset of B'

Question Number : 78 Question Id : 8318968118 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

Which of the following commands is used to delete all rows and free up space from a table?

Options :

1. ✘ Drop
2. ✘ Delete
3. ✔ Truncate
4. ✘ Alter

Question Number : 79 Question Id : 8318968119 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

\_\_\_\_\_ uses Quantifiers that can be either Existential ( $\exists$ ) or Universal ( $\forall$ ).

Options :

1. ✘ Domain Relational Calculus

2. ✓ Tuple Relational Calculus

3. ✘ Distributed Relational Calculus

4. ✘ NoSQL

Question Number : 80 Question Id : 8318968120 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

The database design that consists of multiple tables that are linked together through matching data stored in each table is called a \_\_\_\_\_.

Options :

1. ✓ Relational database

2. ✘ Network database

3. ✘ Object oriented database

4. ✘ Hierarchical database

Question Number : 81 Question Id : 8318968121 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

The incremental model of software development is \_\_\_\_\_.

Options :

1. ✘ a reasonable approach when requirements are well defined

2. ✔ a good approach when a working core product is required quickly

3. ✘ the best approach to use for projects with large development teams

a revolutionary model that is not used for commercial products

4. ✘

Question Number : 82 Question Id : 8318968122 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes Correct Marks : 1 Wrong Marks : 0

The cyclomatic complexity metric provides the designer with information regarding number of\_\_\_\_\_.

Options :

cycles in the program

1. ✘

errors in the program

2. ✘

independent logic paths in the program

3. ✔

statement in the program

4. ✘

Question Number : 83 Question Id : 8318968123 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes

Correct Marks : 1 Wrong Marks : 0

In the spiral model of software development, the primary determinant in selecting activities in each iteration is \_\_\_\_\_.

Options :

1. ✘ iteration size
2. ✘ cost
3. ✔ risk
4. ✘ adopted process such as rational unified process or extreme programming

Question Number : 84 Question Id : 8318968124 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

The optimizer that explores the space of all query-evaluation plans is called \_\_\_\_\_.

Options :

1. ✓ cost-based
2. ✘ plan-based
3. ✘ estimate-based
4. ✘ count-based

Question Number : 85 Question Id : 8318968125 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

The term that optimizes subexpressions shared by different expressions in a program is called \_\_\_\_\_.

Options :

1. ✘ multiple subexpression elimination
2. ✓ common subexpression elimination

parametric subexpression elimination

3. ✘

shared subexpression elimination

4. ✘

Question Number : 86 Question Id : 8318968126 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

Frequency of failure and network recovery time after a failure are  
measures of the \_\_\_\_\_ of a network.

Options :

performance

1. ✘

reliability

2. ✔

security

3. ✘

feasibility

4. ✘

Question Number : 87 Question Id : 8318968127 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

A Gantt chart is least useful for tracking\_\_\_\_\_.

Options :

1. ✘ task dependencies
2. ✘ resource allocation
3. ✘ critical path
4. ✔ code complexity

Question Number : 88 Question Id : 8318968128 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

Which phase of the SDLC typically consumes the most resources?

Options :

Requirements gathering

1. ✘

Testing

2. ✘

Maintenance

3. ✔

Coding

4. ✘

Question Number : 89 Question Id : 8318968129 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

Regression testing is performed to ensure that\_\_\_\_\_.

Options :

new code doesn't break existing functionality

1. ✔

all paths are covered

2. ✘

3. ✘ users accept the system

4. ✘ compliance with laws

Question Number : 90 Question Id : 8318968130 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

The COCOMO model estimates \_\_\_\_\_.

Options :

1. ✘ project risk

2. ✔ software cost

3. ✘ team productivity

4. ✘ user satisfaction

Question Number : 91 Question Id : 8318968131 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes

Correct Marks : 1 Wrong Marks : 0

At which OSI layer does MAC address filtering occur?

Options :

1. ✘ Network
2. ✔ Data Link
3. ✘ Transport
4. ✘ Physical

Question Number : 92 Question Id : 8318968132 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes

Correct Marks : 1 Wrong Marks : 0

Token Ring networks avoid collisions by\_\_\_\_\_.

Options :

1. ✘ CSMA/CD

2. ✓ Token passing

3. ✘ Exponential backoff

4. ✘ Priority queuing

Question Number : 93 Question Id : 8318968133 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

Which routing algorithm guarantees shortest paths even with negative edge weights?

Options :

1. ✘ Dijkstra's

2. ✓ Bellman-Ford

3. ✘ Link-State

4. ✘ OSPF

Question Number : 94 Question Id : 8318968134 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

A TCP header includes all except \_\_\_\_\_.

Options :

1. ✘ Sequence number

2. ✘ Checksum

3. ✔ TTL

4. ✘ Window size

Question Number : 95 Question Id : 8318968135 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

The three-way handshake in TCP ensures \_\_\_\_\_.

Options :

1. ✘ Encryption setup
2. ✔ Synchronized sequence numbers
3. ✘ QoS negotiation
4. ✘ Multicast membership

Question Number : 96 Question Id : 8318968136 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

An IPv4 datagram with header length=5 and total length=400 bytes carries \_\_\_\_\_.

Options :

1. ✔ 380 bytes payload

2. ✘ 400 bytes payload

3. ✘ 20 bytes header

4. ✘ 320 bytes payload

Question Number : 97 Question Id : 8318968137 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

Which protocol uses port 53 by default?

Options :

1. ✘ HTTP

2. ✘ FTP

3. ✔ DNS

4. ✘ SMTP

Question Number : 98 Question Id : 8318968138 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

A switch differs from a hub because, it\_\_\_\_\_.

Options :

1. ✘ operates at Layer 1
2. ✘ broadcasts all frames
3. ✔ uses MAC tables for forwarding
4. ✘ only supports half-duplex

Question Number : 99 Question Id : 8318968139 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

Digital signatures provide\_\_\_\_\_.

Options :

1. ✘ confidentiality
2. ✔ non-repudiation
3. ✘ key exchange
4. ✘ firewall bypass

Question Number : 100 Question Id : 8318968140 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

In asynchronous transmission, the gap time between bytes is \_\_\_\_\_.

Options :

1. ✘ fixed
2. ✔ variable

3. ✘ a function of the data rate

4. ✘ zero

Question Number : 101 Question Id : 8318968141 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

In Java, when we implement an interface method, it must be declared as \_\_\_\_\_.

Options :

1. ✘ private

2. ✘ protected

3. ✔ public

4. ✘ friend

Question Number : 102 Question Id : 8318968142 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes

Correct Marks : 1 Wrong Marks : 0

Which of the following control fields in TCP header is used to specify whether the sender has no more data to transport.

Options :

1. ✓ FIN

2. ✗ RST

3. ✗ SYN

4. ✗ PSH

Question Number : 103 Question Id : 8318968143 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

In XML, DOCTYPE declaration specifies to include a reference to \_\_\_\_\_ file.

Options :

1. ✘ document type declaration
2. ✔ document type definition
3. ✘ document type language
4. ✘ document transfer definition

Question Number : 104 Question Id : 8318968144 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

The CSS used inside HTML elements alongside style attribute is called \_\_\_\_\_.

Options :

1. ✘ external CSS
2. ✘ internal CSS

3. ✓ inline CSS

4. ✘ outline CSS

Question Number : 105 Question Id : 8318968145 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

A web client sends a request to a web server. The web server transmits a program to that client and is executed at client which creates a web document. Such web documents are\_\_\_\_\_.

Options :

1. ✘ dynamic

2. ✘ static

3. ✓ active

4. ✘ passive

Question Number : 106 Question Id : 8318968146 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

Cascading Style Sheets define style and appearance using\_\_\_\_\_.

Options :

1. ✘ functions with parameters and return values
2. ✔ rules with selectors, properties and their values
3. ✘ techniques with block and inline elements
4. ✘ heuristics with rules and maps

Question Number : 107 Question Id : 8318968147 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

What is the correct HTML for making a hyperlink?

Options :

1. ✓ `<a href="http:// abc.com">abc</a>`

2. ✗ `<a name="http://abc.com">abc</a>`

3. ✗ `<http://abc.com</a>`

4. ✗ `url="http://abc.com">`

Question Number : 108 Question Id : 8318968148 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

What is the correct HTML for adding a background color?

Options :

1. ✗ `<body color="yellow">`

2. ✓ `<body bgcolor="yellow">`

3. ✘ `<background>yellow</background>`

4. ✘ `<body background="yellow">`

Question Number : 109 Question Id : 8318968149 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

Which is the correct syntax to link XML file with CSS?

Options :

1. ✘ `<?xml type="text/css" href="file.css"?>`

2. ✘ `<?xml type="text/css" src="file.css"?>`

3. ✓ `<?xml-stylesheet type="text/css" href="file.css"?>`

<?xml-stylesheet type="text/css" src="file.css"?>

4. ✘

Question Number : 110 Question Id : 8318968150 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

A Session variable is created\_\_\_\_\_.

Options :

when the application is first placed on a web server.

1. ✘

when the web server is first started.

2. ✘

when the first client requests a URL resource.

3. ✘

every time a new client interacts with the web application.

4. ✔

Question Number : 111 Question Id : 8318968151 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

Let  $A, B$  be two events and  $\bar{A}$  be the complement of  $A$ . If

$P(\bar{A}) = 0.7, P(B) = 0.7$  and  $P(B|A) = 0.5$ , then  $P(A \cup B) = \underline{\hspace{2cm}}$

Options :

1. ✘ 0.65
2. ✔ 0.85
3. ✘ 0.75
4. ✘ 0.50

Question Number : 112 Question Id : 8318968152 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

Let a random variable  $X$  have a binomial distribution with mean 8 and standard deviation 2. If  $P(X < 2) = \frac{k}{2^{16}}$ , then the value of  $k$  is \_\_\_\_\_

Options :

1. ✓ 17

2. ✘ 16

3. ✘ 136

4. ✘ 137

Question Number : 113 Question Id : 8318968153 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

Let  $A = \{1,2,3\}$ . Which of the following is the number of distinct relations on  $A$ ?

Options :

1. ✘ 256

2. ✘ 158

3. ✓ 512

4. ✘ 1024

Question Number : 114 Question Id : 8318968154 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

In any Lattice L,  $((a \wedge b) \vee a) \wedge b =$  \_\_\_\_\_

Options :

1. ✘  $a \vee b$

2. ✓  $a \wedge b$

3. ✘  $(a \wedge b) \vee a$

4. ✘  $((a \vee b) \wedge a) \vee b$

Question Number : 115 Question Id : 8318968155 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

If the system of linear equations  $x + 2y + z = 5$ ,  $2x + \lambda y + 4z = 12$ ,  $4x + 8y + 12z = 2\mu$  have infinite number of solutions, then the values of  $\lambda$  and  $\mu$  are \_\_\_\_\_

Options :

1. ✘  $\lambda = 4, \mu = 28$
2. ✔  $\lambda = 4, \mu = 14$
3. ✘  $\lambda = 8, \mu = 14$
4. ✘  $\lambda = 8, \mu = 28$

Question Number : 116 Question Id : 8318968156 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

If the product and sum of eigenvalues of a  $2 \times 2$  matrix  $\begin{pmatrix} 3 & x \\ x & y \end{pmatrix}$  are  $-3$  and  $5$ , respectively, then  $x + y =$  \_\_\_\_\_

Options :

1. ✘  $-5$

2. ✘  $-6 \pm i3\sqrt{2}$

3. ✘  $-2 \pm i3$

4. ✔  $-1$

Question Number : 117 Question Id : 8318968157 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

Given that the value of the integral  $\int_1^9 (x^2 - 2) dx$  calculated using the Simpson's 1/3 rule with four uniform subintervals over the interval  $[1,9]$  is given by  $f(1) + \alpha^2 + \frac{8}{3}$ , then the possible value of  $\alpha$  is \_\_\_\_\_

Options :

1. ✔  $\alpha = 15$

2. ✘  $\alpha = 14$

3. ✘  $\alpha = 13$

4. ✘  $\alpha = 12$

Question Number : 118 Question Id : 8318968158 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

$$\lim_{x \rightarrow 1} \left( \frac{x^x - x}{x - 1 - \log x} \right) = \underline{\hspace{2cm}}$$

Options :

1. ✘ 0

2. ✘ 1

3. ✔ 2

4. ✘  $1/2$

Question Number : 119 Question Id : 8318968159 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

Which of the following integral is un-bounded?

Options :

1. ✘  $\int_0^{\pi/4} \tan(x) dx$

2. ✘  $\int_0^{\infty} xe^{-x} dx$

3. ✔  $\int_0^a \frac{1}{a-x} dx$

4. ✘  $\int_0^{\infty} xe^x dx$

Question Number : 120 Question Id : 8318968160 Question Type : MCQ Option Shuffling : Yes Display Question Number : Yes  
Correct Marks : 1 Wrong Marks : 0

Let  $f(x) = x^3 - \frac{9}{2}x^2 + 6x - 2$  be a function defined on the closed interval  $[0,3]$ . Then, the global maximum value of  $f(x)$  is \_\_\_\_\_

Options :

1. ✘ 4.5
2. ✘ 0.5
3. ✔ 2.5
4. ✘ 3.0